

ZyXEL ES-2108-G V3.60(ABL.2)C0

Release Note/Manual Supplement

Date: April 13, 2006

This document describes the features in the ES-2108-G product for its 3.60(ABL.2)C0 release.

Support Platforms:

ZyXEL ES-2108-G V3.60(ABL.2)C0 supports models: ZyXEL ES-2108-G

Version:

ZyNOS F/W Version: V3.60(ABL.2) | 04/13/2006

Bootbase Version: V1.01 | 09/02/2005

Default Bootbase Setting:

ZyNOS Version	V3.60(ABL.2) 04/13/2006 14:03:23
Bootbase Version	V1.01 09/02/2005 14:00:16
Vendor Name	ZyXEL
Product Model	ES-2108-G
ZyNOS Code Model	ES2108G
HTP Code Model	Unknown
ZyNOS ROM address	bfc10000
System Type	8
MAC Address	001349000001
Default Country Code	FF
Boot Module Debug Flag	01
RomFile Version	52
RomFile Checksum	fa15
ZyNOS Checksum	b0ab
SNMP MIB level & OID	060102030405060708091011121314151617181920
Main Feature Bits	C0
Other Feature Bits	
F3 00 00 00 00 00 00 00 00-00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00-00 00 13 00 00 00	

Enhanced Features:

Bug Fix:

Known Issue:

1. For the same ports, LACP and RSTP cannot be activated at the same time.
2. The counter of packets whose length is between 1519 and 1522 (without VLAN tag but including FCS) will be counted both in the range of 1024 to 1518 and Giant.

3. The device will be too busy to responding if it is still learning VLAN from GVRP and configuring the VLAN table. After the process of configuring VLAN table is done, the device will still work well.

Limitation of Settings:

1. VLAN 1Q static entry 256
2. Static MAC forwarding entry 256
3. MAC filtering entry 256
4. Cluster member 24
5. Management IP address 64

Change History:

V3.60(ABL.2) (04/13/2006)
Support new revision of switch chip.

V3.60(ABL.1) (01/13/2006)
Support NetAtlas Enterprise 1.02

V3.60(ABL.0) (09/22/2005)
First Public version

ZyXEL ES-2108-G V3.60(ABL.1)C0

Release Note/Manual Supplement

Date: January 13, 2006

This document describes the features in the ES-2108-G product for its 3.60(ABL.1)C0 release.

Support Platforms:

ZyXEL ES-2108-G V3.60(ABL.1)C0 supports models: ZyXEL ES-2108-G

Version:

ZyNOS F/W Version: V3.60(ABL.1) | 01/13/2006
Bootbase Version: V1.01 | 09/02/2005

Default Bootbase Setting:

ZyNOS Version	V3.60(ABL.1) 01/13/2006 14:32:59
Bootbase Version	V1.01 09/02/2005 14:00:16
Vendor Name	ZyXEL
Product Model	ES-2108-G
ZyNOS Code Model	ES2108G
HTP Code Model	Unknown
ZyNOS ROM address	bfc10000
System Type	8

MAC Address	001349000001
Default Country Code	FF
Boot Module Debug Flag	01
RomFile Version	52
RomFile Checksum	fa15
ZyNOS Checksum	84fe
SNMP MIB level & OID	060102030405060708091011121314151617181920
Main Feature Bits	C0
Other Feature Bits	
F3 00 00 00 00 00 00 00 00-00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00-00 00 13 00 00 00	

Enhanced Features:

1. Support NetAtlas Enterprise 1.02.

Known Issue:

1. For the same ports, LACP and RSTP cannot be activated at the same time.
2. The counter of packets whose length is between 1519 and 1522 (without VLAN tag but including FCS) will be counted both in the range of 1024 to 1518 and Giant.
3. The device will be too busy to responding if it is still learning VLAN from GVRP and configuring the VLAN table. After the process of configuring VLAN table is done, the device will still work well.

Limitation of Settings:

1. VLAN 1Q static entry 256
2. Static MAC forwarding entry 256
3. MAC filtering entry 256
4. Cluster member 24
5. Management IP address 64

Change History:

V3.60(ABL.1) (01/13/2006)
Support NetAtlas Enterprise 1.02

V3.60(ABL.0) (09/22/2005)
First Public version

ZyXEL ES-2108-G V3.60(ABL.0)C0

Release Note/Manual Supplement

Date: September 22, 2005

This document describes the features in the ES-2108-G product for its 3.60(ABL.0)C0 release.

Support Platforms:

ZyXEL ES-2108-G V3.60(ABL.0)C0 supports models: ZyXEL ES-2108-G

Version:

ZyNOS F/W Version: V3.60(ABL.0) | 09/22/2005

Bootbase Version: V1.01 | 09/02/2005

Default Bootbase Setting:

ZyNOS Version	V3.60(ABL.0) 09/22/2005 11:35:49
Bootbase Version	V1.01 09/02/2005 14:00:16
Vendor Name	ZyXEL
Product Model	ES-2108-G
ZyNOS Code Model	ES2108G
HTP Code Model	Unknown
ZyNOS ROM address	bfc10000
System Type	8
MAC Address	001349000001
Default Country Code	FF
Boot Module Debug Flag	01
RomFile Version	52
RomFile Checksum	fa15
ZyNOS Checksum	e180
SNMP MIB level & OID	060102030405060708091011121314151617181920
Main Feature Bits	C0
Other Feature Bits	
F3 00 00 00 00 00 00 00 00-00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00-00 00 13 00 00 00	

Features:

1. MAC address learning
2. Support IEEE 802.1D transparent bridge
3. Support IEEE 802.1Q tagged VLAN
4. Support Port-based VLAN
5. Support IEEE 802.1X
6. Support IEEE 802.1W
7. Support IEEE 802.3AD
8. Support GVRP
9. IGMP snooping
10. Support IEEE 802.1p
11. Automatic age out
12. Specific MAC addresses forwarding per port
13. MAC Filtering
14. Port Trunking
15. Port Mirroring
16. Bandwidth Control
17. Broadcast Storm Control
18. Support Strict Priority and WRR queuing method
19. Static IP management or dynamic IP(DHCP client)
20. Multiple IP address management
21. Firmware upgrade and configuration backup/restore.
22. Remote manageable.
23. Cluster Management
24. WEB manageable
25. Support RFC-1213 MIB II

26. Support RFC-1493 Bridge MIB
27. Support RFC-1643 Ethernet MIB
28. Support RFC-1757 Four group of RMON
29. Support RFC-2674 VLAN MIB
30. NEW CLI supported
31. System configuration backup / restore in text-mode
32. Multiple login supported
33. Radius management authentication
34. SSH/SSL support

Known Issue:

1. For the same ports, LACP and RSTP cannot be activated at the same time.
2. The counter of packets whose length is between 1519 and 1522 (without VLAN tag but including FCS) will be counted both in the range of 1024 to 1518 and Giant.
3. The device will be too busy to responding if it is still learning VLAN from GVRP and configuring the VLAN table. After the process of configuring VLAN table is done, the device will still work well.

Limitation of Settings:

1. VLAN 1Q static entry 256
2. Static MAC forwarding entry 256
3. MAC filtering entry 256
4. Cluster member 24
5. Management IP address 64

Change History:

V3.60(ABL.0) (09/22/2005)
First Public version

Firmware Upgrade:

The ES-2108-G uses FTP to upgrade firmware in run-time through its built-in FTP server. You can use any FTP client (for example, [ftp.exe](#) in Windows) to upgrade ES-2108-G. The upgrade procedure is as follows:

Upgrade ES-2108-G FW:

```
C:\> ftp <ES-2108-G IP address>
User : <Enter>
Password: 1234
230 Logged in
ftp> put 360ABL0C0.bin ras
ftp> bye
```

Where

- User name : just press <Enter>
- Password : the management password, 1234 by default
- 360ABL0C0.bin : the name of firmware file you want to upgrade
- ras : the internal firmware name in ES-2108-G

Configuration Upgrade:

The ES-2108-G uses FTP to upgrade firmware in run-time through its built-in FTP server. You can use any FTP client (for example, [ftp.exe](#) in Windows) to upgrade ES-2108-G. The upgrade procedure is as follows:

Upgrade ES-2108-G configuration:

```
C:\> ftp <ES-2108-G IP address>
User : <Enter>
Password: 1234
230 Logged in
ftp> put 360ABL0C0.rom rom-0
ftp> bye
```

Where

- User name : just press <Enter>
- Password : the management password, 1234 by default
- 360ABL0C0.rom : the name of configuration file you want to upgrade
- rom-0 : the internal configuration name in ES-2108-G