



- Conversion between different transmission speeds and media types
- Built-in fiber transceiver module with SC connector
- Auto-negotiating Ethernet port (Speed and Half/Full Duplex)
- Auto-crossover Ethernet port (supports Auto MDI/MDI-X)
- Build in Link Loss Forwarding Technology to notify the peers if a link goes down
- Easier configuration with DIP Switch
- Switching architecture supports store-and-forward mode
- LED Status Display



Media Converter

MC100FX
-SC

Benefits

Easy Installation

The Auto-negotiating Ethernet function empowers the MC100FX-SC2 / 30 RJ-45 port to negotiate transmission speed and mode with peer devices automatically; and the Auto-crossover Ethernet port can prevent circuit mismatch problems by auto-sensing MDI/MDIX configuration. With these intelligent functions, MC100FX-SC2 / 30 can be paired with a switch, a NIC (Network Interface Card) or a Gigabit Ethernet device via a UTP/STP cable easily.

Easy Troubleshooting

With the Link Loss Forwarding mechanism activated, any detected broken link on the RJ-45 Ethernet port will force the fiber port to take over, and the fiber uplink port will stop transmitting then "turned off" as soon as the remote link is down. Transparent link status will be delivered by the Link Loss Forwarding mechanism to facilitate the troubleshooting process.

Standard Compliance

Connector & Interface

Switch Architecture

Fiber Parameters

Transparent Packet

Link Loose Forward

DIP Switch

LED Indication

Power

Dimension

Operation Environment

EMC

Safety

MC100FX-SC2

MC100FX-SC30

Specifications

System Specifications

- IEEE802.3 10BASE-T
- IEEE802.3u 100BASE-TX
- IEEE802.3x Flow Control and Back pressure
- Fiber: Duplex SC
- RJ-45 Port: CAT-5 (10/100Mbps) Twisted Pair cable Auto MDI/MDI-X and Auto-Negotiation Function Support
- Store-and-Forward
- Fiber Core
 - Multi-Mode (62.5/125um, 50/125um) / Single-Mode (8/125um, 10/125um)
- Wavelength:
 - 1310nm (Multi-mode) / 1310nm (Single-mode)
- Fiber Distance:
 - Multi-Mode Fiber (2KM) / Single-Mode Fiber (30 KM)
- 64 to 1518 Bytes for Non-VLAN Ethernet packet
- 68 to 1522 Bytes for VLAN-Tag type Ethernet packet
- TX to Fiber: If TX port link down, then converter will force fiber to link down.
- Fiber to TX: If Fiber port link down, the media converter will force TX port to link down.
- DIP Switch 1: UTP auto-Negotiation / 100Mbps Full Duplex mode
- DIP Switch 2: Fiber Full/Half duplex
- DIP Switch 3: LLF (Link Lose Forwarding) Disable / Enable
- DIP Switch 4: Switch converter / Pure converter mode
- Module: PWR,100, LNK/Act, FDX/COL
- Stand-alone (external adapter):DC 9V / 0.7A
- 119 (L) x 85 (D) x 26 (H) mm
- Operating temperature: 0°c ~ 45°c
- Storage temperature: - 10°c ~ 70°c
- Operating humidity: 10% ~ 90%, non-condensing

Certifications

- FCC Part15 (Class A)
- CE EMC (Class A)
- UL , cUL

Product Description

A media converter with SC connector and multimode fiber transceiver module built-in; and is capable of extending network span up to 2km.

A media converter with SC connector and singlemode fiber transceiver module built-in; and is capable of extending network span up to 30km.

For more product information, visit us on the web www.ZyXEL.com

Corporate Headquarters

ZyXEL Communications Corp.
Tel: +886-3-578-3942
Fax: +886-3-578-2439
Email: sales@zyxel.com.tw
<http://www.zyxel.com>

ZyXEL Denmark A/S
Tel: +45 39 55 07 00
Fax: +45 39 55 07 07
Email: sales@zyxel.dk
<http://www.zyxel.dk>

ZyXEL France SARL
Tel: +33 (0)472529797
Fax: +33 (0)472521920
Email: info@zyxel.fr
<http://www.zyxel.fr>

ZyXEL Hungary
Tel: +36-1-336-1646
Fax: +36-1-325-9100
Email: info@zyxel.hu
<http://www.zyxel.hu>

ZyXEL North America
Tel: +1-714-632-0882
Fax: +1-714-632-0858
Email: sales@zyxel.com
<http://www.us.zyxel.com>

ZyXEL Russia
Tel: +7 (095) 542-8920
Fax: +7 (095) 542-8925
Email: info@zyxel.ru
<http://www.zyxel.ru>

ZyXEL Sweden A/S
Tel: +46 (0) 31 744 77 00
Fax: +46 (0) 31 744 77 01
Email: sales@zyxel.se
<http://www.zyxel.se>

ZyXEL Ukraine
Tel: +380 44 494 49 31
Fax: +380 44 494 49 32
Email: sales@ua.zyxel.com
<http://www.ua.zyxel.com>

ZyXEL Czech s.r.o.
Tel: +420 241 091 350
Fax: +420 241 091 359
Email: info@cz.zyxel.com
<http://cz.zyxel.com>

ZyXEL Finland Oy
Tel: +358-9-4780 8400
Fax: +358-9-4780 8448
Email: sales@zyxel.fi
<http://www.zyxel.fi>

ZyXEL Germany GmbH.
Tel: +49 (0) 2405-6909 0
Fax: +49 (0) 2405-6909 99
Email: sales@zyxel.de
<http://www.zyxel.de>

ZyXEL Kazakhstan
Tel: +7-327-2-590-699
Fax: +7-327-2-590-689
Email: sales@zyxel.kz
<http://www.zyxel.kz>

ZyXEL Norway A/S
Tel: +47 22 80 61 80
Fax: +47 22 80 61 81
Email: sales@zyxel.no
<http://www.zyxel.no>

ZyXEL Spain
Tel: +34 902 195 420
Fax: +34 913 005 345
Email: sales@zyxel.es
<http://www.zyxel.es>

ZyXEL UK Ltd.
Tel: +44 (0) 1344 303044
Fax: +44 (0) 1344 303034
Email: sales@zyxel.co.uk
<http://www.zyxel.co.uk>

